SECTION 264313 - TRANSIENT-VOLTAGE SUPPRESSION FOR LOW-VOLTAGE ELECTRICAL POWER CIRCUITS

PART 1 - GENERAL

1.1 SUMMARY

A. Section includes field-mounted TVSS for low-voltage (120 to 600 V) power distribution and control equipment.

1.2 SUBMITTALS

A. Product Data: For each type of product indicated. Include rated capacities, operating weights, electrical characteristics, furnished specialties, and accessories.

B. Field quality-control reports.

C. Operation and maintenance data.

D. Warranties: Sample of special warranties.

1.3 QUALITY ASSURANCE

A. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by a testing agency, and marked for intended location and application.

B. Comply with IEEE C62.41.2 and test devices according to IEEE C62.45.

C. Comply with NEMA LS 1.

D. Comply with UL 1449.

E. Comply with NFPA 70.

1.4 WARRANTY

A. Special Warranty: Manufacturer's standard form in which manufacturer agrees to repair or replace components of surge suppressors that fail in materials or workmanship within specified warranty period.

1. Warranty Period: Five years from date of Substantial Completion.

PART 2 - PRODUCTS

2.1 SERVICE ENTRANCE SUPPRESSORS

A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:

1. ABB USA.
2. AC Data Solutions.
3. Advanced Protection Technologies Inc. (APT).
4. Atlantic Scientific.
5. Current Technology Inc.; Danaher Power Solutions.
6. Danaher Power Solutions; United Power Products.
7. Eaton Electrical Inc.; Cutler-Hammer Business Unit.
8. General Electric Company; GE Consumer & Industrial - Electrical Distribution.
9. Intermatic, Inc.
10. LEA International.
11. Leviton Mfg. Company Inc.
12. Liebert Corporation; a division of Emerson Network Power.
13. Northern Technologies, Inc.; a division of Emerson Network Power.
14. Siemens Energy & Automation, Inc.
15. Square D; a brand of Schneider Electric.
16. Surge Suppression Incorporated.

B. Surge Protection Devices:

1. Non-modular.
2. LED indicator lights for power and protection status.
3. Comply with UL 1449.
4. Fuses, rated at 200-kA interrupting capacity.
5. Fabrication using bolted compression lugs for internal wiring.
6. Redundant suppression circuits.
7. Arrangement with wire connections to phase buses, neutral bus, and ground bus.
8. LED indicator lights for power and protection status.

C. Peak Single-Impulse Surge Current Rating: 160 kA per mode/320 kA per phase.

D. Minimum single impulse current ratings, using 8-by-20-mic.sec waveform described in IEEE C62.41.2

1. Line to Neutral: 70,000 A.
2. Line to Ground: 70,000 A.
3. Neutral to Ground: 50,000 A.

E. Protection modes and UL 1449 SVR for grounded wye circuits with 208Y/120 V, 3-phase, 4-wire circuits shall be as follows:

1. Line to Neutral: 400 V for 208Y/120 V.
2. Line to Ground: 400 V for 208Y/120 V.
3. Neutral to Ground: 400 V for 208Y/120 V.
4. Line to Line: 1000 V for 2084/120 V.

F. Short Circuit Current Rating (SCCR): SCCR at least equal to the available fault current a point of use.

2.2 ENCLOSURES

A. Indoor Enclosures: NEMA 250 Type 1.

B. Outdoor Enclosures: NEMA 250 Type 3R.

PART 3 - EXECUTION

3.1 INSTALLATION

A. Install TVSS devices at service entrance on load side, with ground lead bonded to service entrance ground.

B. Install TVSS devices for panelboards and auxiliary panels with conductors or buses between suppressor and points of attachment as short and straight as possible. Do not exceed manufacturer's recommended lead length. Do not bond neutral and ground.

1. Provide circuit breaker as a dedicated disconnecting means for TVSS as indicated.

3.2 FIELD QUALITY CONTROL

A. Perform tests and inspections.

1. Manufacturer's Field Service: Engage a factory-authorized service representative to inspect components, assemblies, and equipment installations, including connections, and to assist in testing.

B. Tests and Inspections:

1. Perform each visual and mechanical inspection and electrical test stated in NETA ATS, "Surge Arresters, Low-Voltage Surge Protection Devices" Section. Certify compliance with test parameters.
2. After installing TVSS devices but before electrical circuitry has been energized, test for compliance with requirements.
3. Complete startup checks according to manufacturer's written instructions.

C. TVSS device will be considered defective if it does not pass tests and inspections.

D. Prepare test and inspection reports.

3.3 STARTUP SERVICE

A. Do not energize or connect service entrance equipment to their sources until TVSS devices are installed and connected.

B. Do not perform insulation resistance tests of the distribution wiring equipment with the TVSS installed. Disconnect before conducting insulation resistance tests, and reconnect immediately after the testing is over.

3.4 DEMONSTRATION

A. Train Owner's maintenance personnel to maintain TVSS devices.

END OF SECTION 264313